





- Epoxy meets UL-94 V-0 flammability rating
- Moisture Sensitivity Level 1
- High power dissipation capability
- Part no. with suffix “Q” means AEC-Q101 qualified

- Linear voltage regulators Low-side switches
- Battery-driven devices MOSFET drivers
- Amplifiers

- : SOT-223
- Tin plated leads, solderable per J-STD-002 and JESD22-B102
- BCP51-16



(Example)

BCP51-16Q	F-	Approximate	,	2500	5000	F F'



■ (Ta=25 unless otherwise noted)

Collector-Emitter Voltage	V_{CEO}	V	-45
Collector-Base Voltage	V_{CBO}	V	-45
Emitter-Base Voltage	V_{EBO}	V	-5
Collector Current	I_C	A	-1
Power Dissipation (*)	P_D	W	1.5
Thermal Resistance From Junction To Ambient (*)	R_{dJA}	/W	83.3
Thermal Resistance From Junction To Solder Point	R_{dJS}	/W	16
Operation Junction Temperature	T_j		-55 to +150
Storage Temperature	T_{stg}		-55 to +150

(*) Device mounted on FR-4 PCB 1.575 x 1.575 x 0.0625 inch; mounting pad for collector =0.93 sq in

■ (Ta=25 unless otherwise noted)

Collector-base breakdown voltage	V_{CBO}	V	$I_C = -100\mu A, I_E = 0$	-45	-	-
Collector-emitter breakdown voltage	V_{CEO}	V	$I_C = -10mA, I_B = 0$	-45	-	-
Emitter-base breakdown voltage	V_{EBO}	V	$I_E = -100\mu A, I_C = 0$	-5	-	-



4
BV

14

14

t

14

A

BV

E

V

V

V

V

V

V

V

V

V

V

V

(Typical)




Fig.3 - Collect-Emitter Saturation Voltage



C B



The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with automotive electronics are not designed for use in medical, life-saving, life-sustaining, or military, Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's sales office for further assistance.